































Maximum Allowable Distance on Monorail System

Monorail (12V Only)

SL Power Supply	 7W LED MR16 / LMPD7	 4W LED MR16 / LMPD4	 8W LED MR16 / LMPD8	Soraa 7W and 9.5W
PWE60NLF (Filtered) PWE60NL PWESMT60LED PWERM60D(LED) PWESMT150A(LED) PWESMT300A(LED) Must include run length, powerfeed length and if using a remote transformer, the distance from input connection to the transformer	<20ft			
	 3W LED G4 Bi-Pin / LMPL3	 3W LED MR11 / LMPD3	 2W LED G4 Bi-Pin / LMPL2	
	<25ft		<25ft Only use Filtered PWE60NLF, PWESMT60LED, PWERM60D(LED)	
PWERM150D(LED) PWERM300D(LED) No Load Must include run length, powerfeed length and distance from input connection	 7W LED MR16 / LMPD7	 4W LED MR16 / LMPD4	 8W LED MR16 / LMPD8	Soraa 7W and 9.5W
	<40ft			
	 3W LED G4 Bi-Pin / LMPL3	 3W LED MR11 / LMPD3	 2W LED G4 Bi-Pin / LMPL2	
<50ft				
PWMSMT150	 7W LED MR16 / LMPD7	 4W LED MR16 / LMPD4	 8W LED MR16 / LMPD8	Soraa 7W and 9.5W
	<75ft			
	 3W LED G4 Bi-Pin / LMPL3	 3W LED MR11 / LMPD3	 2W LED G4 Bi-Pin / LMPL2	
<75ft				
PWMSMT300 PWMSMT600	 7W LED MR16 / LMPD7	 4W LED MR16 / LMPD4	 8W LED MR16 / LMPD8	Soraa 7W and 9.5W
	<50ft			
	 3W LED G4 Bi-Pin / LMPL3	 3W LED MR11 / LMPD3	 2W LED G4 Bi-Pin / LMPL2	
<50ft				
PWMRM150 PWMRM300 PWMRM600 Must include run length, powerfeed length and distance from input connection	 7W LED MR16 / LMPD7	 4W LED MR16 / LMPD4	 8W LED MR16 / LMPD8	Soraa 7W and 9.5W
	12V Tap @ 150W <50ft 12V Tap @ 300W <25ft 13V Tap @ 150W <75ft 13V Tap @ 300W <40ft 14V Tap @ 150W <150ft 14V Tap @ 300W <75ft 15V Tap @ 150W <200ft 15V Tap @ 300W <100ft			
	 3W LED G4 Bi-Pin / LMPL3	 3W LED MR11 / LMPD3	 2W LED G4 Bi-Pin / LMPL2	
12V Tap @ 150W <50ft 12V Tap @ 300W <25ft 13V Tap @ 150W <75ft 13V Tap @ 300W <40ft 14V Tap @ 150W <150ft 14V Tap @ 300W <75ft 15V Tap @ 150W <200ft 15V Tap @ 300W <100ft				